



SNAP-IN BREAKERS

480 PRIMARY VOLTS — 240/120 SECONDARY VOLTS — 1Ø, 60 Hz

Single Phase

kVA	Catalog Number	Secondary Maximum Circuit ①		Height (Inches)(Cm.)	Width (Inches)(Cm.)	Depth (Inches)(Cm.)	Weight (Lbs.)(Kg.)
		120 V (1-pole)	240 V (2-pole)				
3.0	PT061150003LS	8	4	32.13 (81.6)	13.25 (33.7)	7.63 (19.4)	120 (54.4)
5.0	PT061150005LS	8	4	32.13 (81.6)	13.25 (33.7)	7.63 (19.4)	120 (54.4)
7.5	PT061150007LS	8	4	32.13 (81.6)	15.88 (40.3)	11.00 (27.9)	160 (72.6)
10.0	PT061150010LS	8	4	34.38 (87.3)	15.88 (40.3)	11.00 (27.9)	185 (83.9)
15.0	PT061150015LS	12	6	34.38 (87.3)	17.13 (43.5)	12.38 (31.4)	240 (109.0)
25.0	PT061150025LS	20	10	41.88 (106.4)	17.88 (45.4)	13.50 (34.3)	330 (150.0)

① The number of secondary circuits shown is only a representation of circuits. Please contact the factory for exact number of secondary circuits available.

304 STAINLESS STEEL/ SNAP-IN BREAKERS

480 PRIMARY VOLTS — 240/120 SECONDARY VOLTS — 1Ø, 60 Hz

Single Phase

kVA	Catalog Number	Secondary Maximum Circuit ①		Height (Inches)(Cm.)	Width (Inches)(Cm.)	Depth (Inches)(Cm.)	Weight (Lbs.)(Kg.)
		120 V (1-pole)	240 V (2-pole)				
5.0	PT061150005SS	8	4	32.13 (81.6)	13.25 (33.7)	7.63 (19.4)	120 (54.4)
7.5	PT061150007SS	8	4	32.13 (81.6)	15.88 (40.3)	11.00 (27.9)	160 (72.6)
10.0	PT061150010SS	8	4	34.38 (87.3)	15.88 (40.3)	11.00 (27.9)	185 (83.9)
15.0	PT061150015SS	12	6	34.38 (87.3)	17.13 (43.5)	12.38 (31.4)	240 (109.0)
25.0	PT061150025SS	20	10	41.88 (106.4)	17.88 (45.4)	13.50 (34.3)	330 (150.0)

① The number of secondary circuits shown is only a representation of circuits. Please contact the factory for exact number of secondary circuits available.

SNAP-IN BREAKERS

480 VOLTS to 240/120 VOLTS

Circuit Breaker Data

kVA	480 Volts primary breakers	240/120 Volts secondary main	Maximum Rating of Secondary Breakers
3.0	ED42B025L (25A)	Q225 (25A)	20 amps
5.0	ED42B025L (25A)	Q225 (25A)	20 amps
7.5	ED42B025L (25A)	Q240 (40A)	30 amps
10.0	ED42B035L (35A)	Q250 (50A)	40 amps
15.0	ED42B050L (50A)	Q270 (70A)	60 amps
25.0	ED42B090L (90A)	Q2125 (125A)	100 amps